# Inter-Tech Elektronik Handels GmbH

## SAMA FTX-1000-A Armor



#### SAMA FTX-1000-A Armor – gold power for your PC

The 1000W powerful power supply from SAMA is 80PLUS® Gold certified and equipped with the latest technology! The DC/DC technology ensures maximum efficiency and stable voltages. With the +12V single-rail technology, a full 81A is also available for power-hungry graphics cards. 105°C-certified A+ premium capacitors from Nichicon Japan offer maximum reliability for well over 100.000 operating hours (MTBF) with over 90% efficiency.

The fully modular cable design offers a free choice in terms of connections. In addition to two 4+4-pin connections for dual-CPU systems, the SAMA FTX-1000-A Armor has nine S-ATA, three Molex and four PCIe 6+2-pin connections, all of which have a flat-cable design, which contributes to a clean cable management in the case.

The smooth-running, temperature-controlled 120mm fan, which reliably cools the inner workings of the power supply, sits in the high-quality power supply housing, which has been provided with golden aluminum applications. A 60 month manufacturer's guarantee rounds off the overall package and underlines the high quality of the SAMA FTX-1000-A Armor.

- √ 80PLUS® Gold with more than 90% efficiency
- √+12V single-rail technology with 81A
- ✓ DC/DC technology
- √ full modular cable design
- √ 60 months warranty



## SAMA FTX-1000-A Armor

Output Mainboard 20+4Pin 4Pin/ 4+4Pin/ 8Pin 12V	1000\ 1
4Pin/ 4+4Pin/ 8Pin 12V	_
	- / 2x /
PCI-Express 6+2Pin	7 = 7
PCI-Express 6Pin	4
IDE 4Pin	3
S-ATA	9
Floppy	
Fan monitoring	
100/240V Input	•/
PFC	(auto
ATX-Standard	2.·
Fan dimension	1x 120mn
Fan control	Automati
Noise level	19-22di
Cable management	
Protection circuit	OVP, OCP, SCP, NLI
PSU dimensions (H/W/D)	86/150/180mn
Package dimensions (H/W/D)	130/330/195mn
Weight (net)	1.88k
Weight (gross)	3.20kg
Packing units (VE/VPE/PAL)	1/6/14
Warranty	60 Month
Article number	8888219
EAN-Code	426045564677
Scope of delivery	Bag with modular cables, Power cord Screws, Manual (german, english
	Screws, Manual (german, english

- = existing = non existing

### **Connectors**

